

LEAD-FREE / RoHS-COMPLIANT

DIRECTIONAL COUPLER

C10-0667

The C10-0667 is a broadband 6-67 GHz, 10 dB directional coupler. The multisection tri-plate stripline design exhibits excellent coupling flatness and VSWR at all ports. Custom designs are also available, contact the factory for details.

Features

- Ultra Broadband Performance
- Excellent Coupling Flatness
- High Directivity
- Low VSWR
- Microwave Power Dividers & Couplers App Note




Electrical Specifications

Parameter ¹	Frequency Range (GHz)	Min	Тур	Max
Mean Coupling (dB)	6-67		10	
Amplitude Flatness (dB) ²			±0.8	
Direct Line Insertion Loss (dB)	DC-67			2.5
VSWR	6-30		1.2	1.45
	30-67		1.5	
Directivity (dB)	6-30	13	17	
	30-67	8	13	
Weight (g)			25	

¹Specifications guaranteed when operated in a 50Ω system.

²Deviation from average coupling.



215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com



DIRECTIONAL COUPLER

C10-0667

Page 2

Typical Performance




Fig. 1. Direct line insertion loss.




Fig. 3. Coupled port power.




Fig. 2. Typical port return loss.




Fig. 4. Typical directivity.



DIRECTIONAL COUPLER

C10-0667

Page 3

Model Number	Description	
C10-0667	6-67 GHz 10 dB Directional Coupler with 1.85 mm connectors ¹ , LEAD-FREE/RoHS COMPLIANT	

¹Default is 1.85 mm female connectors. Consult factory for other connector options.

Revision History

Revision code	Revision Date	Comment
В	4/2020	Updated Direct Line IL specs

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice.

Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.